

Release Notes

hp StorageWorks Command View EVA

Product Version: 3.2

Second Edition (July 2004)

Part Number: AA-RT6YF-TE

This document contains the most recent product information about the HP StorageWorks Command View EVA 3.2 software and documentation.

For the latest version of these Release Notes and other storage documentation, access the HP storage web site at <http://www.hp.com/country/us/eng/prodserv/storage.html>.



© Copyright 1998-2004 Hewlett-Packard Development Company, L.P.

Hewlett-Packard Company makes no warranty of any kind with regard to this material, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose. Hewlett-Packard shall not be liable for errors contained herein or for incidental or consequential damages in connection with the furnishing, performance, or use of this material.

This document contains proprietary information, which is protected by copyright. No part of this document may be photocopied, reproduced, or translated into another language without the prior written consent of Hewlett-Packard. The information contained in this document is subject to change without notice.

Microsoft®, MS-DOS®, MS Windows®, Windows®, and Windows NT® are U.S. registered trademarks of Microsoft Corporation.

UNIX® is a registered trademark of The Open Group.

Solaris® is a registered trademark of Sun Microsystems, Inc.

Hewlett-Packard Company shall not be liable for technical or editorial errors or omissions contained herein. The information is provided "as is" without warranty of any kind and is subject to change without notice. The warranties for Hewlett-Packard Company products are set forth in the express limited warranty statements for such products. Nothing herein should be construed as constituting an additional warranty.

Printed in the U.S.A.

Command View EVA Release Notes
Second Edition (July 2004)
Part Number: AA-RT6YF-TE

Release notes contents

These release notes cover the following major topics:

- [Intended audience](#), page 3
- [System support information](#), page 4
- [Browser support](#), page 8
- [Operating constraints](#), page 10
- [Avoiding problem situations](#), page 14
- [Command View EVA v3.2 known issues](#), page 16
- [SMI-S EVA v3.2 information](#), page 21

Intended audience

This document is intended to assist customers who are installing or using HP StorageWorks Command View Enterprise Virtual Array (EVA) v3.2 in conjunction with an installation of a HP StorageWorks EVA3000 or EVA5000.

System support information

This section contains information about the prerequisites for running Command View EVA v3.2 software and the documentation available for use with Command View EVA v3.2 and related products.

Command View EVA v3.2 minimum software requirements

Before you install Command View EVA v3.2, you must install the software listed in [Table 1](#). The table shows the minimum version of the software required and explains how to check the current version.

Table 1: Minimum software requirements

Software	Minimum Version Required	How to Check Current Version
HP StorageWorks Virtual Controller Software (VCS)	ENT-v2.006 for Enterprise Virtual Array 5000 ENT-v2.006 for Enterprise Virtual Array 3000	In Command View EVA: Expand an Initialized Storage Cell . Expand the Hardware Folder . Expand Rack1 . Expand Controller Enclosure . Select either controller. Verify that the Software Version field displays ENT-V2.006 or ENT-V2006 .
HP OpenView Storage Management Appliance Software	v2.1	From the Storage Management Appliance Home Page: Click Help on the Storage Management Appliance primary toolbar. View the version number displayed on the Welcome page.
Visit the Storage Management web site at: http://h18006.www1.hp.com/products/sanworks/managementappliance/index.html and download all mandatory updates and patches.		

Enterprise Virtual Array documentation

Enterprise Virtual Array documentation is available at

<http://h18006.www1.hp.com/storage/arraysystems.html>

On this web site:

1. Under **Virtual Array Systems**, select your EVA model.
2. Select **Technical Documentation** under **Product Information**.

Software compatibility matrices

The Enterprise Virtual Array uses various firmware and software that work with each other to manage the storage solution. During installation, it is important to ensure that all of the software and firmware versions are compatible. This section provides tables that summarize which versions of software are compatible with each other. Use [Table 2](#), [Table 3](#), and [Table 4](#) to ensure that you are using compatible software versions.

The HP StorageWorks Command View EVA v3.2 software is compatible with the following:

Software

- HP StorageWorks Virtual Controller Software v3.020 (recommended version)
- HP OpenView Storage Management Appliance software v2.1

Hardware

- HP OpenView Storage Management Appliance
- HSV110 controller (EVA5000)
- HSV100 controller (EVA3000)

[Table 2](#) lists the compatible versions of element manager software and storage system software. Command View EVA v3.2 is compatible with several versions of VCS; however, the required VCS version is VCS v3.020. If you are running a version of VCS that is not listed in this table (for instance, VCS v1.01), you should upgrade to a later version of VCS.

Note: After you have upgraded a storage system to v3.000 (or higher), you should not downgrade the initialized storage system to v2.xxx. If you attempt to downgrade an initialized storage system, you will lose any configuration information or data in that storage system. All existing data will be destroyed when you downgrade from v3.xxx to v2.003 (or higher).

Table 2: Element Manager software and Storage System software compatibility

Storage System Software Version	HSV Element Manager v2.0a	Command View EVA v2.1	Command View EVA v3.0	Command View EVA v3.0a	Command View EVA v3.1	Command View EVA v3.2
VCS v2.002	Yes	Yes	Yes	Yes	Yes	Yes
VCS v2.003	No	Yes	Yes	Yes	Yes	Yes
VCS v2.004	No	Yes	Yes ¹	Yes ¹	Yes ¹	Yes
VCS v2.005	No	Yes	Yes	Yes	Yes	Yes
VCS v2.006	No	Yes	Yes	Yes	Yes	Yes
VCS v3.000	No	No	Yes ²	Yes ²	Yes ²	Yes
VCS v3.001	No	No	Yes	Yes	Yes	Yes
VCS v3.010	No	No	No ³	No ³	Yes	Yes
VCS 3.014	No	No	No	No	Yes	Yes
VCS v3.020	No	No	No	No	No	Yes
¹ VCS v2.004 is compatible only with EVA3000. ² VCS v3.000 cannot be used on an EVA3000 system. ³ While Command View EVA v3.0, v3.0a, and v3.1 can manage controllers running VCS v3.020, you will not have access to any v3.020-specific features. HP recommends that you upgrade to Command View EVA v3.2.						

[Table 3](#) lists the versions of VCS each Enterprise Virtual Array is compatible. The EVA3000 storage system uses the HSV100 controller, and the EVA5000 storage system uses the HSV110 controller.

Table 3: Enterprise Virtual Array type and VCS compatibility

	EVA3000	EVA5000
VCS v2.002	No	Yes
VCS v2.003	No	Yes
VCS v2.004	Yes	No
VCS v2.005	Yes	Yes
VCS v2.006	Yes	Yes
VCS v3.000	No	Yes
VCS v3.001	No	Yes
VCS v3.010	Yes	Yes
VCS v3.014	Yes	Yes
VCS v3.020	Yes	Yes

Table 4 lists the compatible versions of element manager software and Storage Management Appliance software. Command View EVA v3.2 is compatible with the Storage Management Appliance software v2.1. If you are running Storage Management Appliance software v1.0c or Storage Management Appliance software v2.0, you must upgrade the Storage Management Appliance software to v2.1.

Table 4: Element Manager software and Storage Management Appliance software compatibility

Storage Management Appliance Software	HSV Element Manager v2.0a	Command View EVA v2.1	Command View EVA v3.0	Command View EVA v3.0a	Command View EVA v3.1 and v3.2
v1.0C	Yes	No	No	No	No
v2.0	Yes	Yes* *requires Service Pack 1a.	Yes* *requires Service Pack 3.	Yes* *requires Service Pack 4	No
v2.1	No	No	No	Yes	Yes

For future product support release information, visit

<http://welcome.hp.com/country/us/eng/prodserv/storage.html>

This web site provides downloadable files for storage products.

To download future Storage Management Appliance updates, visit

<http://h18006.www1.hp.com/products/sanworks/managementappliance/index.html>

You can access the latest update by choosing **Software Updates** under **Product Information**.

Browser support

Table 5 describes browser support by operating system. Using browser versions other than the recommended versions could result in some pages not displaying correctly (blank or distorted pages) or some buttons not working.

Table 5: Browser support by operating system

Operating System	CV EVA Browser	JRE Version
Windows NT 4.0 SP6a	Internet Explorer 6.0 SP1	JRE 1.4.1_03, JRE 1.4.1_04
Windows 2000 Server and Advanced Server SP3	Internet Explorer 6.0 SP1	JRE 1.4.1_03, JRE 1.4.1_04
Sun Solaris 8, 9	Netscape 7.0	JRE 1.4.1_03, JRE 1.4.1_04
HP-UX 11i, 11.23	Netscape 7.0	JRE 1.4.1_02, JRE 1.4.1_04
Red Hat Linux AS 2.1 (32)	Netscape 7.02	JRE 1.4.1_03, JRE 1.4.1_04
Windows Server 2003 (IA32)	Internet Explorer 6.0 (v6.00.3790.0000)	JRE 1.4.1_03, JRE 1.4.1_04

Configuration restriction for HSG and HSV controllers in a heterogeneous SAN environment

HP recommends that one Storage Management Appliance manage a maximum of 25 HSG and 16 HSV storage systems.

Product enhancements

This release contains the following product enhancements:

- The user can select the drive type (online or near-online) in the user interface.
- Cross Vraid snap functionality.

Operating constraints

This section contains operating constraints for HP StorageWorks Command View EVA v3.2.

Command View EVA v3.2 cannot be uninstalled

The installation process cannot be cancelled, and once the installation is completed, the product cannot be uninstalled.

Handling an installation failed message

If you receive an **Installation Failed** message during installation, retry the installation. If the error persists, contact your authorized HP service representative for assistance.

When upgrading to CV EVA v3.2 from CV EVA v3.0 or an earlier version of CV EVA, you may see a message stating `Install is Complete` followed three lines later by a message stating `Install is Aborted`. In this situation, the installation has failed.

Command View EVA, SSSU, and VCS version matrix

Table 6 shows the versions of Command View EVA and the versions of Storage System Scripting Utility (SSSU) and VCS supported by those versions.

Table 6: Command View EVA, SSSU, and VCS version matrix

Command View EVA Version	SSSU Version	VCS Version
2.0a, 2.1	v4 Build 18	2.0xx
3.0	Build 72 for version 3.0	2.0xx, 3.0xx
3.1	Build 8 for version 3.01	2.0xx, 3.0xx
3.2	Build 6 for version 3.2	2.0xx, 3.0xx

Browser settings

This section contains information and details to help ensure that your browser configuration is correct for this product.

Deleting temporary Internet files

Before using Command View EVA v3.2 for the first time, delete the temporary Internet files in your browser. To do this in Internet Explorer:

1. Select **Tools/Internet Options**.
2. Click **Delete Files** on the **General** tab.
3. Click **OK**
4. Restart your browser.

Browser refresh required after agent upgrade

To load the latest client code in your browser, refresh the browser after upgrading Command View EVA.

- To refresh your browser in Internet Explorer, press **CTRL + F5**.
- To refresh your browser in Netscape, press and hold **Shift** and click **Reload**.

System color setting

When accessing Command View EVA v3.2 with Internet Explorer or Netscape, set the display properties colors setting to True Colors or 16,000,000 colors.

Page caching

For the best performance of Command View EVA v3.2, enable page caching. Page caching is allowed only in an HSV-only environment. Page caching is not allowed in heterogeneous environments (for example, HSG and HSV).

Follow the steps appropriate for your browser to check or enable page caching.

Enabling Page Caching in Internet Explorer 6.x

1. Open Internet Explorer and choose **Tools/Internet Options**.
2. Click **Settings** on the **General** tab.
3. On the Settings page, choose **Automatically** in the **Check for newer versions of stored pages** option.
4. Ensure that a Temporary Internet Files folder is selected and that it is at least 10 MB in size.
5. Click **OK** until you return to the main browser window.

Enabling Page Caching in Netscape 7.x

1. Open Netscape and choose **Edit/Preferences/Advanced/Cache**.
2. At the bottom of the dialog box, set the **Compare the page in the cache to the page on the network** option to **Every time I view the page**.
3. Ensure that the **Disk Cache** setting is at least 100,000 KB.
4. Ensure that the **Memory Cache** setting is at least 1000 KB.
5. Click **OK**.

Browser behavior

Be aware of the following considerations when using browsers.

The right-click menu in some browser configurations is disabled. If you are in a configuration where right-clicking brings up a menu, do not use the **Internet Explorer Open Link in New Window, Save Target As, Set as Desktop Item**, or **Add to Favorites** options or their Netscape equivalents. These links will lead you back into the GUI without the proper context and cause incorrect information to display.

Tuning navigation tree performance

Command View EVA v3.2 displays information about your storage system in the form of a navigation tree located in the Navigation pane of your browser window. The tree shows the condition of and relationships among the objects in your storage area network (SAN). Large tree structures (in large SAN environments) display more slowly than smaller structures. This can cause a performance problem.

You can tune the performance of your navigation tree by setting the number of tree objects displayed at one time. The default number of **tree objects displayed** is 100.

- For configurations with a small number of objects, set the number to a value higher than the number of objects in your SAN. By doing this, the management agent will send the complete tree structure to your browser each time you click on the tree. This provides good performance in smaller environments.
- For configurations with a larger number of objects, set the number to a smaller number (20-50) of objects. By doing this, the management agent will send only a small number of objects to your browser each time you click on the tree. Your browser will display a special page and scroll buttons in the navigation tree, allowing you to request the display of other tree segments.

To set the number of tree objects displayed:

1. Click **Agent Options**.
2. Click **User Interface Options**.
3. Set the number of objects displayed in the **Tree objects displayed** field.
4. Click **Save Changes**.
5. Click **OK**.

Browsing from HP-UX/Netscape

In some instances when browsing from HP-UX using Netscape, the Storage Management Appliance responds with the Login page, but the page does not contain the two input boxes for Username and Password, and you cannot proceed. In this situation, you can browse directly to Command View EVA v3.2 using the following URL

<http://YourApplianceName:2381/ResEltCpgFusion>

Snapshot allocation policy

All snapshots within a virtual disk family must have the same allocation policy. For example, if a snapshot is created using **Allocate on Demand**, all snapshots within that virtual disk family must also be allocated on demand. The same requirement applies if the first snapshot is created using the **Allocate Completely** allocation policy. That is, all subsequent snapshots within that family must be fully allocated.

Moving objects between folders-SSSU restriction

In the Command View EVA GUI, you can move objects between folders. This feature is not supported in SSSU.

Vdisk command completion

When you submit Vdisk commands, remember that commands will complete in the order in which they were issued (sequentially) regardless of the amount of time required to process a particular command.

Configuring the number of events to gather on failover

If your Command View EVA system is configured to allow failover to a passive Command View EVA, be aware of this performance consideration.

The number of events first collected after taking control has been restricted. This minimizes the performance impact on your storage system after taking control.

The default is to collect a history of only the last 100 events. You can change this value by changing the `Maximum_events` parameter in the `PASSIVE_MANAGER` section of the `NsaServer.ini` file in `C:/hsvmafiles`.



Caution: Do not change any other parameters in this file.

Avoiding problem situations

This section describes how to avoid problem situations specific to Command View EVA v3.2.

Setting preferred path when creating snapclones

Setting the preferred path during the creation of a snapclone will change the preferred path of the original virtual disk to that of the snapclone being created. If you want the original virtual disk to have a different preferred path, HP recommends you set the preferred path to the same path as the original virtual disk and then set the preferred path for the snapclone after creation.

Note: If you create a snapclone without selecting the preferred path, the default of **No Preference** will be given to both the original virtual disk and the snapclone.

Managing EVAs with multiple appliances

If you have multiple storage management appliances, HP strongly recommends that all of your EVAs be managed by a single storage management appliance at any given time.

Avoiding slow response times and timeouts caused by multiple Command View EVA v3.2 users

To avoid timeouts or slow response times, HP recommends the following.

- Only one user at a time on Command View EVA v3.2
- Only one SSSU session at a time on Command View EVA v3.2
- Do not use the Command View EVA v3.2 GUI if SSSU is being used to run controller failovers.

Sorting in the navigation tree

When objects in the current view are renamed, the view is not resorted. The object maintains its current order on the tree. When subsequent objects are created, the placement is affected by the changed object's name. The result is incorrect alphabetical sorting in the **Navigation** tree. Restart Command View EVA v3.2 to correct the problem.

Setting Enterprise Virtual Array controller time

HP recommends that the Enterprise Virtual Array controller time be set to the same time as the Storage Management Appliance for the following reasons.

- Setting the controller and Storage Management Appliance time to the same time enhances troubleshooting capability.
- Choosing the **re-synch controller time** option will reduce time synchronization problems due to drift.
- The **custom time** option sets the controller time. If it is set to a time other than the Storage Management Appliance time, you can expect event synchronization problems.

See the *Command View EVA v3.2 Online Help* for the time setting procedure.

Navigation tree collapses or opens spontaneously

If you want to leave the Command View EVA v3.2 user interface but want the display to remain static, choose a non-expandable HSV storage system object (such as an empty virtual disk folder in the **Navigation** tree) as your last action. If you do not have a non-expandable storage system object, create one.

If your last navigation tree action was to open or close a container object, the navigation tree might spontaneously collapse or open when the system automatically refreshes.

Unknown Storage System

In some instances, Command View EVA may display a storage cell as an Unknown Storage System. This state occurs when Command View EVA was previously communicating with the controllers but the controllers have stopped responding. Conditions that can cause this include:

- Controllers are being powered off
- Controllers are restarting
- Controllers are experiencing a heavy I/O load
- Previous operation is taking a long time to complete
- Storage Area Network (SAN) problem exists

The Unknown Storage System condition recovers automatically when Command View EVA is able to communicate again.

Command View EVA v3.2 known issues

This section contains information about known issues in Command View EVA v3.2.

Disk group creation when all available disks are in a warning state

To create a disk group from the user interface, eight ungrouped drives of the same drive type in GOOD condition are required. The creation of a disk group from the SSSU will be successful even if the disks are in a warning state.

Restarting a single controller

The restarted controller will either display in the Unmappable Hardware Folder with a red X or will stay in the Hardware Rack Folder with a red X, even though the controller has been rebooted. Clicking the other controller will display a Lock Busy Error. To remove the red X and to move the controller to the Unmappable Hardware Folder, click the red X.

CV EVA window open when adding copy set via CAUI 1.1a

If the CV EVA window is open when adding a Copy Set via CAUI 1.1a, the CV EVA window will appear to be hung. Once the Copy set is completed, the CV EVA window will be freed.

DR folder warning icon

The Data Replication Folder icon may occasionally show a warning status when there is no problem with any of the DR groups within the folder. Click the DR folder to remove the warning status.

Improper error message (through SSSU) on password-protected systems

When a controller pair has been password-protected and the password has not been added in Bridge, SSSU commands will display Error: API unable to get the lock.

Entering a new password in Bridge

Users can enter a new password when JRE 1.4.2 is installed and enabled.

Warning triangle displayed after Vraid recovery

After Vraid recovery, the yellow warning triangle may still be displayed. Refreshing the screen will eradicate the problem.

Using a Linux Host

If you are using a Linux host with Command View EVA, and you attempt to add a host using the Add a Host page in the user interface, you will see no Linux choice in the Host OS field. In this case, use Sun Solaris in the Host OS field.

Previous button fails to work

When using the Initialize Advanced Options pages in the user interface, the Previous button may not appear to work. This is a browser configuration issue caused by enabling the **Do not save encrypted pages to disk** option in the **Tools/Internet Options/Advanced/Security** menu. Disabling this option allows the button to work.

Progress indicator dots in user interface

Progress indicator dots in the user interface will not display correctly unless you have chosen the **Play animations** option after selecting the **Tools/Internet Options/Advanced/Multimedia** menu of your Internet Explorer browser.

Upgrade status page does not display

During an upgrade from VCS v2.0x to VCS v3.0x, the success status page may not display, and the upgrade may or may not have succeeded. You may see an error page stating that the command could not be completed. If this occurs:

1. Click **OK** on the error page.
2. Browse to the HSV on which you attempted the upgrade.
3. View the **System Version** on the Initialized System Properties page. If the displayed value is 3.0x, the upgrade was successful.
4. If you do not see the value of 3.0x, go to the Session pane.
5. Click on **Agent Options**.
6. Choose **Discover Storage Systems**.
7. Click **OK**.

If the upgrade still did not succeed, repeat the code load process.

Changing the Management Appliance password

You cannot change the Management Appliance password from within Command View EVA. To change the password on the Management Appliance:

1. From the **Agent Options** screen, choose **Remote Access Password Options**.
This will redirect you to the **Management Appliance Home Page**.
2. Under the **Settings** tab, navigate to the **Change Password** screen.
3. Change the password on this screen.

Windows Server 2003 security settings

The security setting in your browser must be properly configured to allow access to the objects on the browser pages. To do this:

1. Click **Start**.
2. Click **Control Panel**.
3. Click **Java Plug-in**.
4. Click the **Browser** tab.

Choose the browser you plan to use with Command View EVA.

Get Log File Option

The **Get Log File** option on the Management Agent Events, Controller Events, and Controller Termination Events pages (accessed from the View Events page) is for HP authorized service representative use only.

Disk names higher than disk count

Adding disks, removing disks, or changing the storage cell Device Addition property from Manual to Automatic may cause disks to be named and renamed. Command View EVA v3.2 ensures that disk names are distinct by incrementing the last three digits of the name. This naming method can result in disks named with a number higher than the total disk count for a particular system.

For example, if you have five disks named disk 001 through disk 005, and remove disk 003 and disk 004, the next time you insert 003 and 004 disks, Command View EVA v3.2 will name them 006 and 007.

SSSU responds with server down error while still able to browse to Command View EVA v3.2

In rare instances, SSSU loses communication with Command View EVA v3.2 and reports that it is down, stopped, or restarting even though it is possible to browse to Command View EVA v3.2. To fix this, restart Command View EVA v3.2.

SSSU responds with neither success nor failure message

In some instances when SSSU is run from a host with a heavy I/O load, SSSU may issue the following error:

```
Error: Neither SUCCESS or FAILURE were returned by this command.
```

If this error occurs, verify the success or failure of the command, then retry the command, if necessary. If the error persists, contact your HP authorized service representative for troubleshooting assistance.

Page not found/Connection lost/neither success nor failure error

You may experience a condition where the symptom is an HTTP 404 - File not found error in the browser or what appears to be a hung state in SSSU. The SSSU state may generate a No Object Found error or a Neither Success or Failure error. To resolve this:

- Wait a few seconds and the problem may resolve itself or
- Close all of your open browser windows, including the Storage Management Appliance and Command View EVA windows. SSSU does not need to be restarted.

If the problem persists after these steps, restart Command View EVA v3.2.

Command View EVA v3.2 startup time

The larger your storage environment, the longer it will take to start Command View EVA v3.2.

Scrolling function

In rare situations, the scrolling function of the navigation tree may not respond. If you encounter this behavior, refresh your browser window.

Netscape and time settings

Because of differences in the time functions running in Netscape browsers on Unix platforms, controller clock displays on the system property pages may be incorrect. With some versions of Unix, the time may be off by the Greenwich Mean Time (GMT) offset of the browser computer's geographic location. With other Unix versions, the time may just be incorrect.

Because of this issue, time displays on the **Set Time** page and **Initialize an HSV Storage system page 2** page have been suppressed when viewed with a Netscape browser. Also, the **local browser time** option is unavailable from Netscape. If you want to use your browser's local time, you can set it as a custom time in these pages.

Management Appliance time setting

The **Set System Time** allows you to set the storage system's clock. The default starting selection is always **Use Management Appliance Date/Time** even though this may not be what is currently implemented.

Online help behavior with Netscape

The online help provided with Command View EVA may behave erratically when viewed with Netscape. Also, the index and search functions may not operate properly.

Netscape tooltips

Tooltips (pop-up displays) do not work in some Unix implementations of Netscape.

Security/password issue with Storage Management Appliance v2.1

When you change the user name or password for a Storage Management Appliance v2.1, the internal Command View EVA v3.2 user name and password are not changed. SSSU still accesses the Storage Management Appliance and executes element manager commands using the old user name and password (such as administrator/administrator). This can be confusing as you will not be prompted to enter the Command View EVA v3.2 internal user name and password unless the browser cookie expires.

To change the internal user name and password for Command View EVA v3.2, browse directly to http://<appliance_name> or ip:2381/cpqlogin.htm?ChangePassword=yes

Event log messages use HSV Element Manager name

Storage Management Appliance event log messages may refer to Command View EVA by its former name, HSV Element Manager.

Parse file format restrictions on Unix

If you need to use the **send parse file** functionality on a Unix machine, be sure the parse file is in DOS format. If you use FTP to transfer the parse file, use binary mode.

Discovery display issue

Errors may occur during discovery that affect the view of your configuration as displayed by Command View EVA. If you see duplicate storage cells or uninitialized storage cells you know to be initialized, restart Command View EVA. If that does not correct the problem, restart the Storage Management Appliance.

SMI-S EVA v3.2 information

SMI-S EVA v3.2 is supported on Microsoft® Windows® 2000 SP2 and above. SMI-S v3.2 requires that Command View EVA v3.2 be installed on the Storage Management Appliance. Command View EVA v3.2 must be installed before installing SMI-S EVA. If the Storage Management Appliance is running Command View EVA v2.1 or earlier, you must upgrade to Command View EVA v3.2. Refer to *HP StorageWorks Enterprise Virtual Array Updating Product Software Instructions* for more information. You can view the latest copy of this document at

<http://h20000.www2.hp.com/bizsupport/TechSupport/DocumentIndex.jsp>

SMI-S EVA features

SMI-S EVA provides the following features:

■ Profile

- Array

■ Subprofiles

- Access point
- Backend ports
- Cluster
- Copy services
- Location
- LUN creation
- LUN masking and mapping
- Pool manipulation capabilities and settings
- Software

■ Profile

- Server

■ Indications - Events Capabilities

- Process indications
- Lifecycle indications. Following are the lifecycle indications that SMI-S EVA supports:
 - Select * from CIM_InstCreation where SourceInstance ISA CIM_ComputerSystem
 - Select * from CIM_InstDeletion where SourceInstance ISA CIM_ComputerSystem
 - Select * from CIM_InstModification where SourceInstance ISA CIM_StorageVolume and SourceInstance.OperationalStatus < > PreviousInstance.OperationalStatus
 - Select * from CIM_InstModification where SourceInstance ISA CIM_FCPort and SourceInstance.OperationalStatus < > PreviousInstance.OperationalStatus
 - Select * from CIM_InstModification where SourceInstance ISA CIM_ComputerSystem and SourceInstance.OperationalStatus < > PreviousInstance.OperationalStatus

■ Other Features

- Service Location Protocol (SLP) discovery
- Java Authentication and Authorization Service (JAAS) based security
- Secure Sockets Layer (SSL)

SMI-S EVA v3.2 known issues**Hardware WWNs attached to a LUN masking Protocol controller**

The hardware WWNs attached to a LUN masking Protocol controller will have the same OS type.

Creation of a storage pool

Creation of a storage pool does not accept size as a parameter. The storage pool can be created from the given set of storage disks.

Copy services are synchronous

SMI-S EVA does not support the job control subprofile and the indications of the copy services subprofile. All methods in the copy services are synchronous.

SLP component does not work after uninstalling SMI-S EVA

SMI-S EVA removes the SLP component at uninstallation. Any other application that uses the SLP component will not work after uninstalling SMI-S EVA

Support for subprofile

SMI-S EVA supports access points subprofile only for top level computer systems.

LUN masking profile

SMI-S EVA does not support indications for LUN masking subprofile.